



717 SOUTH MYRTLE AVENUE • MONROVIA, CALIFORNIA 91016-3422
626-358-2559 • FAX 626-359-5701 • 800-525-6925

Instructions
TLP-105SYL Telephone Logger Patch
with LED and 15db Gain Audio
P/N 43740 B Series

The TLP-105SYL provides an analog audio connection to recorder from telephones that have modular connected handsets. It provides a clear recording of both sides of your conversation from almost all types of telephones whether they are digital or analog. The TLP-105SYL provides 15db amplification of the audio signal to the recorder.

An ON/OFF switch and indicator LED are provided on the top of the TLP-105SYL. When the switch is in the ON position (away from LED), the indicator will light to show that the audio output is active, and the current conversation is being recorded. With the switch in the opposite position, the LED will be off and the audio output will be disconnected.

To Install: (See diagram on reverse)

1. Disconnect coil cord from base of telephone.
2. Plug coil cord into modular jack on TLP-105SYL.
3. Insert cord from TLP-105SYL into jack on phone base where coil cord was connected.
4. Connect cord going to logger or recorder to larger modular (RJ11) jack on TLP-105SYL (audio is on center pair).
5. Insert the plug on the supplied AC adapter into the "6VDC" receptacle on the TLP-105SYL. The adapter may be plugged into any adjacent 115VAC power outlet. Negative DC polarity is on the center contact of the power plug.
6. Mount unit at a convenient location on base of telephone using the adhesive pad.

Instructions
TLP-105SYL Telephone Logger Patch
with LED and 15db Gain Audio
P/N 43740 B Series

