



11636 GOLDRING RD • ARCADIA, CALIFORNIA 91006-5815
626-358-2559 • FAX 626-359-5701 • 800-525-6925

Instructions TLP-124A/124B Telephone Logger Patch P/N 43760/43830 B Series

The TLP-124A provides an audio connection for recorders to telephones that have modular connected handsets or headsets. It is designed for those phones that have no sidetone, but need both sides of the conversation recorded. The TLP-124A provides a clear connection to both sides of conversations from almost all types of telephones whether they are the new digital based phones or the older analog types. The TLP-124B has 70% more near party gain than the TLP-124A for those that require it.

To install the unit, disconnect the handset coil cord from the base of the telephone and replace it with the mini-mod plug from the TLP-124A. Connect the handset coil cord into the mini-mod jack on the TLP-124A. Connect a line cord from the recorder to the RJ-11 jack on the TLP-124A. Only the two central conductors of the RJ-11 jack (pins 3 & 4) in the unit are connected and carry the audio signal. Plug the 6VDC AC Adapter (P/N 39184), furnished with the unit, into an adjacent utility outlet for 115VAC power. Insert the 1.2mm plug on the power cord into the jack on the TLP-124A. The center contact of the power plug is negative DC polarity. The unit may be mounted at a convenient location on the base of the telephone utilizing the adhesive pad.

