



11636 GOLDRING RD • ARCADIA, CALIFORNIA 91006-5815
626-358-2559 • FAX 626-359-5701 • 800-525-6925

Instructions TLP-124ADJ Telephone Logger Patch For Phones with No Sidetone

The TLP-124ADJ provides an audio connection for recorders to telephones that have no sidetone and have modular connected handsets or headsets, but need both sides of the conversation recorded. The TLP-124ADJ provides a BALANCE CONTROL adjustment that allows the audio signals of the near party (your voice) and far party to be equalized and amplified on the recording output. To adjust the far party louder, turn the BALANCE CONTROL clockwise. See the diagram below.

To install the unit, disconnect the handset coil cord from the base of the telephone and replace it with the mini-mod plug from the TLP-124ADJ. Connect the handset coil cord into the mini-mod jack on the TLP-124A. Connect a line cord from the recorder to the RJ11 jack on the TLP-124A. Only the two central pins of the RJ11 jack (pins 3 & 4) in the unit are connected and carry the audio signal. Plug in the 6VDC AC power supply. The unit may be mounted at a convenient location on the base of the telephone using the adhesive pad.

